

Coreless BLDC motor.

High Power Density - High Efficiency - Cost Effective Low noise - Low inductance - Good Heat Dissipation Long Lifetime - No Cogging - Low Inertia - Robust

Feature

	SVTN A 01-2864-12-S-O
Nominal voltage	12 V
No load speed	7956 rpm
No load current	182 mA
Nominal speed	6712 rpm
Nominal torque	50.000 mNm
Nominal current	3.680 A
Stall torque	320.000 mNm
Stall current	22.600 A
Max. efficiency	82.800 %
Terminal resistance*	0.500 Ω
Terminal inductance*	0.110 mH
Torque constant	14.290 mNm/A
Speed constant	668 mNm/V

Notice: The provided technical data are the higher limits recommended in static condition. To obtain the correct dimensioning of the product, it is necessary to hold account of all the applicable dynamic forces, including the inertia of the manipulator, the configuration of the tools and the external forces applied.

2 POLE BRUSHLESS DC MOTORS

	SVTN A 01-2864-12-S-O
Speed/torque gradient	24.90 rpm/mNm
Mechanical time constant	2.500 ms
Rotor inertia	9.620 gcm²

The bene?ts of this new technology are torque and high-speed when compared to the same sizing. The lack of cogging, a reduced ripple torque, a linear correlation between speed and torque, low inertia bring performance to a greater level in terms of power, dynamics by means of reduced weights and reduced dimensions. Servotecnica's brushless motors apply hall sensors as a standard option, in addition to having the magnetic encoder option. Thanks to the sensors it is possible to control rotation speed, and, thanks to the lack of cogging, provide high performance and accuracy.



Benefits

Winding technology without metal bodies

Good heat dissipation and high overload capacity

Long life expectancy

Light and compact, easy integration

High reliability

Good return on investment

