

Coreless BLDC motor.

High Power Density - High Efficiency - Cost Effective Low noise - Low inductance - Good Heat Dissipation Long Lifetime - No Cogging - Low Inertia - Robust

Feature

	SVTN A 01-4070-12-S-H
Nominal voltage	12 V
No load speed	6154 rpm
No load current	264 mA
Nominal speed	5084 rpm
Nominal torque	130.000 mNm
Nominal current	7.290 A
Stall torque	748.000 mNm
Stall current	40.700 A
Max. efficiency	84.500 %
Terminal resistance*	0.300 Ω
Terminal inductance*	0.110 mH
Torque constant	18.500 mNm/A
Speed constant	516 mNm/V

Notice: The provided technical data are the higher limits recommended in static condition. To obtain the correct dimensioning of the product, it is necessary to hold account of all the applicable dynamic forces, including the inertia of the manipulator, the configuration of the tools and the external forces applied.

2 POLE BRUSHLESS DC MOTORS

	SVTN A 01-4070-12-S-H
Speed/torque gradient	8.20 rpm/mNm
Mechanical time constant	3.400 ms
Rotor inertia	39.430 gcm²

The bene?ts of this new technology are torque and high-speed when compared to the same sizing. The lack of cogging, a reduced ripple torque, a linear correlation between speed and torque, low inertia bring performance to a greater level in terms of power, dynamics by means of reduced weights and reduced dimensions. Servotecnica's brushless motors apply hall sensors as a standard option, in addition to having the magnetic encoder option. Thanks to the sensors it is possible to control rotation speed, and, thanks to the lack of cogging, provide high performance and accuracy.





Winding technology without metal bodies

Good heat dissipation and high overload capacity

Long life expectancy

Light and compact, easy integration

High reliability

Good return on investment

