

variables/V-color

Micromotors | Coreless BLDC motors | SVTN A 01-2240-36-D-O





Feature

SVTN A 01-2240-36-D-O

Nominal voltage	36 V
No load speed	16679 rpm
No load current	73 mA
Nominal speed	14128 rpm
Nominal torque	12.000 mNm
Nominal current	0.670 A
Stall torque	78.000 mNm
Stall current	4.000 A
Max. efficiency	74.700 %
Terminal resistance*	9.100 ?
Terminal inductance*	0.640 mH
Torque constant	20.230 mNm/A
Speed constant	472 mNm/V

Notice : The provided technical data are the higher limits recommended in static condition. To obtain the correct dimensioning of the product, it is necessary to hold account of all the applicable dynamic forces, including the inertia of the manipulator, the configuration of the tools and the external forces applied.

2 Pole Brushless DC Motors

SVTN A 01-2240-36-D-O

Speed/torque gradient	212.60 rpm/mNm
Mechanical time constant	5.100 ms

SVTN A 01-2240-36-D-O

Rotor inertia

2.270 gcm²

The benefits of this new technology are torque and high-speed when compared to the same sizing. The lack of cogging, a reduced ripple torque, a linear correlation between speed and torque, low inertia bring performance to a greater level in terms of power, dynamics by means of reduced weights and reduced dimensions. Servotecnica's brushless motors apply hall sensors as a standard option, in addition to having the magnetic encoder option. Thanks to the sensors it is possible to control rotation speed, and, thanks to the lack of cogging, provide high performance and accuracy.



Advantages

- Winding technology without metal bodies
- Good heat dissipation and high overload capacity
- Long life expectancy



Benefits

- Light and compact, easy integration
- High reliability
- Good return on investment



expertise in connectivity