



Coreless BLDC motor.

High Power Density - High Efficiency - Cost Effective
 Low noise - Low inductance - Good Heat Dissipation
 Long Lifetime - No Cogging - Low Inertia - Robust

 Feature

SVTN A 01-2248-36-D-O	
Nominal voltage	36 V
No load speed	13390 rpm
No load current	82 mA
Nominal speed	11749 rpm
Nominal torque	18.000 mNm
Nominal current	0.790 A
Stall torque	147.000 mNm
Stall current	5.900 A
Max. efficiency	77.800 %
Terminal resistance*	6.100 Ω
Terminal inductance*	0.580 mH
Torque constant	25.320 mNm/A
Speed constant	377 mNm/V

Notice : The provided technical data are the higher limits recommended in static condition. To obtain the correct dimensioning of the product, it is necessary to hold account of all the applicable dynamic forces, including the inertia of the manipulator, the configuration of the tools and the external forces applied.

2 POLE BRUSHLESS DC MOTORS

SVTN A 01-2248-36-D-O

Speed/torque gradient	91.20 rpm/mNm
Mechanical time constant	3.000 ms
Rotor inertia	3.140 gcm ²

The benefits of this new technology are torque and high-speed when compared to the same sizing. The lack of cogging, a reduced ripple torque, a linear correlation between speed and torque, low inertia bring performance to a greater level in terms of power, dynamics by means of reduced weights and reduced dimensions. Servotecnica's brushless motors apply hall sensors as a standard option, in addition to having the magnetic encoder option. Thanks to the sensors it is possible to control rotation speed, and, thanks to the lack of cogging, provide high performance and accuracy.



Advantages

Winding technology without metal bodies

Good heat dissipation and high overload capacity

Long life expectancy



Benefits

Light and compact, easy integration

High reliability

Good return on investment



Zoning de la Rivière, 65
7330 Saint-Ghislain (Belgium)

T : +32 (0)65 76 40 40
E : service@pes-sa.com