



Coreless BLDC motor

Long Lifetime - High Efficiency - Low Noise - High Reliability  
No Cogging - Low Inertia - Cost-effective

 Feature

SVTN A 03-2854-12-S-1	
Nominal voltage	12 V
No load speed	6878 rpm
No load current	121 mA
Nominal speed	5674 rpm
Nominal torque	15.000 mNm
Nominal current	1.040 A
Stall torque	85.700 mNm
Stall current	5.380 A
Max. efficiency	72.300 %
Torque constant	16.300 mNm/A
Speed constant	586 mNm/V

**Notice :** The provided technical data are the higher limits recommended in static condition. To obtain the correct dimensioning of the product, it is necessary to hold account of all the applicable dynamic forces, including the inertia of the manipulator, the configuration of the tools and the external forces applied.

# 2 POLE BRUSHLESS DC MOTORS WITH INTEGRATED ELECTRONICS

SVTN A 03-2854-12-S-1

Speed/torque gradient	80.30 rpm/mNm
Mechanical time constant	4.400 ms
Rotor inertia	5.200 gcm <sup>2</sup>

The benefits of this technology join the simplicity of use of a brushed DC motor with the longevity of a brushless motor, maintaining cost-effectiveness and ease of integration. The lack of cogging is typical of the coreless motors and guarantees a reduced ripple torque, a linear correlation between torque, speed, and low inertia. The miniaturization of the electronics allows maintaining the diameter of the motor unvaried with a slight increase in length.



## Advantages

Winding technology without metal bodies

Good heat dissipation and high overload capacity

Long life expectancy



## Benefits

Light and compact, easy integration

High reliability

Good return on investment

No need for external drive



**pes**

product  
engineering  
services

Zoning de la Rivière, 65  
7330 Saint-Ghislain (Belgium)

T : +32 (0)65 76 40 40  
E : service@pes-sa.com