



Coreless DC Motor

High Power Density - High Efficiency - High Reliability
 Low Inductance - Low Inertia - Good Heat Dissipation
 Long Operational Lifetime - Cost Effective - No Cogging

 Feature

SVTN B 01-1331-03-D-OM	
Nominal voltage	3 V
No load speed	12000 rpm
No load current	45 mA
Nominal speed	9600 rpm
Nominal torque	2.100 mNm
Nominal current	0.900 A
Stall torque	10.300 mNm
Stall current	4400.000 A
Max. efficiency	80.800 %
Terminal resistance*	0.680 Ω
Terminal inductance*	0.050 mH
Torque constant	2.360 mNm/A
Speed constant	4000 mNm/V

Notice : The provided technical data are the higher limits recommended in static condition. To obtain the correct dimensioning of the product, it is necessary to hold account of all the applicable dynamic forces, including the inertia of the manipulator, the configuration of the tools and the external forces applied.

2 POLE BRUSHED DC MOTORS

SVTN B 01-1331-03-D-OM

Speed/torque gradient	1166.10 rpm/mNm
Mechanical time constant	8.000 ms
Rotor inertia	0.650 gcm ²

The specific design construction of a coreless DC motor provides several advantages over the traditional, iron core, technology. A first added value it is given by rotor lower mass and inertia, so very rapid acceleration and deceleration rates are possible. Furthermore, the lack of iron reduces "iron losses" to provide higher efficiencies (up to 90 percent) than traditional DC motors. Last, but not least, the coreless design reduces winding inductance, so sparking between the brushes and commutator is reduced, increasing motor life and reducing electromagnetic interference (EMI). Our Coreless DC Motors are available on a wide range of sizes and we can show high flexibility on custom requirements.



Advantages

Winding technology without metal bodies

Good heat dissipation and high overload capacity

Long life expectancy



Benefits

Light and compact, easy integration

High reliability

Good return on investment



Zoning de la Rivière, 65
7330 Saint-Ghislain (Belgium)

T : +32 (0)65 76 40 40
E : service@pes-sa.com